




TuyaSmart



Wi-Fi







4 WIRE WIFI


VIDEO DOOR PHONE MANUAL

INDOOR MONITOR SPECIFICATION

Note: The following are diagrams of all of the available indoor unit models, not all models have the same layout or features, please take actual model as quasi.



Type B



NO.	Name	Descriptions
1	TFT display	View visitor's image displayed on TFT screen
2	Microphone	Transmit the voice to door station
3	SD card slot	For the models with SD card, Insert the SD card for recording
4	Mechanical button	talk,unlock,monitor,close.

SYSTEM INFO

1. Electrical locks / alarms / cameras are not included in the package, you can buy electrical locks that fit the actual requirements.
2. Built-in or external power supply is optional. Suitable for a wide voltage range (AC100V-240V). Unplug the AC power plug before installing the device. (shown as below)



3. For the use and selection of wires, please refer to the following. (cable quality influence video and voice transfer distance)

- 1). 4C ordinary unshielded wire and shielded wiring

Distance $\leq 30\text{m}$ (RVV4*0.5mm²); Distance $\leq 50\text{m}$ (RVV4*0.75mm²)
 Distance $\leq 70\text{m}$ (RVV4*1.0mm²); Distance $\leq 100\text{m}$ (RVV4*1.5mm²)



- 2). Category 5 network cable connection (not recommended)



(Unshielded network cable distance ≤ 50 meters)


- 3). Category 6 network cable connection.

Category 6 network are the same as Category 5 network, shielded network cable distance ≤ 100 meters.


Wiring Diagram



First monitor must be set as **master**. all other monitors must be set as **slave**. this can be done in the settings menu. **monitor id setting**
master=01, slave=02 to 04



Type A




Product Information

Monitor Feature

1. System Capacity: 4 indoor monitors + 2 door stations + 2 cameras.
2. Intercom Mode: Two-way intercom, cloud intercom.
3. Function: Video communication, monitor, unlock, image memory/video record, wifi, TUYAAPP, and motion detection.
4. Resolution: 1024*600.
5. Screen: 7"/10" TFT LCD touch screen.
6. Talking time: 60 seconds.
7. electric current: Standby current 130mA; working current 360mA.
8. Power supply: External power DC12-15V ; Built-in power AC180-240V.
9. Work Temperature: -10~50 .
10. Max Capacity: 128G.

Monitor Interface

Main Interface



The diagram illustrates the transition from the Start Interface to the Main Interface. The Start Interface shows the word "WELCOME" in a stylized font. An arrow points to the Main Interface, which displays a digital clock (23:24), the date (Nov.26.2021 Wednesday), and a row of six navigation icons: Monitor, CCTV, Intercom, PlayBack, Unlock, and Leave home. The Main Interface also includes a settings gear icon in the top left and status icons (signal, battery, Wi-Fi) in the top right.


Start Interface

Main Interface

Note. Enter the main interface in 15 seconds after Charge the power to the wifi monitor.

Operating instructions

Main Interface Instruction



The diagram shows the Main Interface with numbered callouts (1-11) pointing to specific UI elements:

- 1: Monitor icon
- 2: CCTV icon
- 3: Intercom icon
- 4: PlayBack icon
- 5: Unlock icon
- 6: Leave home icon
- 7: Time display (23:24)
- 8: Wi-Fi status icon
- 9: Battery status icon
- 10: Signal strength icon
- 11: Settings gear icon

- | | | | |
|--|---|--|--|
| 1 Monitor
Monitor image of the door station. | 2 CCTV
Monitor image of the camera. | 3 Intercom
Call and intercom other monitors. | 4 playback
Image memory and video view |
| 5 gate
Lock which connect to indoor monitor. | 6 Mode
3 modes, At home, Leave home, Dormancy | 7 Time and Date Display | 8 Wifi Status |
| 9 Memory SD card Status | 10 Alarm sensor status | 11 Setting | |

Intercom

- Click Intercom to call other monitor ID



Mode(At Home, Leave Home, Dormancy)


- At Home, Leave Home, Dormancy



Operating instructions


Playback

- Click Playback to view the image and video



CCTV Monitor Interface

- Click here for monitor




- | | | | |
|--|---------------------------------|-------------------------------|---|
| 1 Switch
Switch of the CCTV monitor. | 2 Photo
Snap pictures | 3 Record
Take video | 4 Back
Exit/Return |
| 5 Time and Date | 6 monitor time countdown | 7 CCTV ID | 8 color, brightness, contrast adjustment |

Operating instructions

Communication and Monitor Interface


- Click here for monitor and communication





- | | | | |
|---|---|-------------------------------|--|
| 1 Switch
Switch of the outdoor station monitor. | 2 Photo
Snap pictures | 3 Record
Take video | 4 Answer |
| 5 Unlock
Lock which connect to outdoor station. | 6 Back
Exit/Return | 7 Time and Date | 8 monitor and talk time countdown |
| 9 Door ID | 10 Ring tone, call sound, color, brightness, contrast adjustment | | |

Operating instructions


Setting

- Click  to enter setting interface
Recording, Wi-Fi, Volume, Storage, Date&Time, Display, Others




1 Recording


- Auto recording(video or photo)





- Motion Detection



- Always monitoring(Each camera monitors the time)



2 Wi-Fi




- Wifi On/off and selection.

- Input WIFI password

Operating instructions


3 Volume

- Click Volume to enter setting interface. Set the volume, ring type, and ring time.



4 Storage

- Clear storage space. Format of SD card, and delete all videos or pictures.




5 Date/Time

- System Time
- Sync time
Press the button, the time of device 1 can be synchronized to device 2, device 3, and device 4.



6 Display

- Standby mode or cleaning mode or Screen brightness selection.
- LCD OFF (The screen goes black after 30 seconds of operation).
- Lock screen wallpaper (The system comes with lock screen scrolling wallpaper).



7 Others

- There are nine languages: English, Korean, Chinese, Hebrew, Russian, Spanish, Turkish, Polish, Czech, Arabic.
- Extension ID: Range from 1 to 4. 1 means the monitor is Master, 2 to 4 means the indoor monitors are slave. Each family support 4 indoor monitors maximum.
- Unlock time: The unlocking time of the outdoor station. The range is 1s-10s, and the default is 2s.
- Security password: Security alarm password. When the alarm signal is triggered, the alarm can be canceled through the password. The password can be changed.
- Security: CCTV1 and CCTV2 both have a normally closed security zone. Turn on the zone function. When the zone is in an open state, the indoor unit will give a warning.
- System reset: Indoor unit restores initialization status.
- System: Including version information, version release date, UUID, SD memory.

TUYAAPP adding and connection.

Mobile Phone TUYAAPP Setting, make sure the mobilephone is nearby the wifi monitor and router.




Step 1

the mobile phone connect the same wifi with the monitor wifi. And down load the APP“Tuya Smart” in google player or IOS APP store.


Step 2

clicking the “Tuya Smart” APP for adding




Step 3

Searching and pairing




Step 4

wifi monitor device is found and click“add”




Step 5

Being added




Step 6

added successfully and click “Done”



Step 7


Mode Setting after added device




HOW TO SHARE “Tuya Smart ” TO OTHER USERS

new home members need to register the new account
follow the below steps to share.


Step 1




Step 2



Step 4



Step 3



Step 5

Cancel **Add Member** Save

another registered user name

Name **gghhv**

Region China >

Account **+86-15217163981**

another user registration
account(phone number or email)

Only after accepting the invitation will the account owner be able to use all the functions.

Family Role Common Member >

Step 6

< **Home Settings**

Home Name **my home** >

Room Management 0 Room(s) >

Home Location >

Home Member **the new member is added**

gghhv
Waiting to join...

info
info@zhuian.cn Home Owner >

Add Member

Delete Home

Step 6 for finish adding and checking

How to Share to additional users.

Preparation: new home members need to register the new account

the steps of the share to additional users as the below.

Open the "TUYA SMART" APP on the mobile phone ----- click "me" ----- click "home management"
----- click "my home" to enter the "Home Setting" ----- click "Add Member" ----- click "App Account"
----- input the registered user name and account(email or phone number) and Save it You will find the
new additional users at the "Home Setting".

APP intercom instruction

